

# Leslie®

## LS2215 KEYBOARD AMPLIFIER

The LESLIE brand has become an icon, synonymous with high quality in sound, performance, construction and reliability. The LESLIE LS2215 Combo Amplifier upholds the Leslie tradition now in a compact *non-rotary* model designed to compliment any keyboard rig, solo performer, acoustic guitarist, or other application where powerful, clean amplification is desired.

*The LS2215 features a 200 watt solid state mono power amp with a pair of 4" mid-high drivers and a 15" woofer. The stereo preamp section features 3 discrete input channels, Instrument, Keyboard, and Microphone; each with independent 3-band EQ. The **Instrument and Keyboard** channels each feature L&R stereo 1/4" input jacks, while the **Microphone** channel features 1/4" and XLR jacks.*

*The Instrument and Keyboard channels include independent stereo send and return jacks, for effects management. A fourth channel a **Stereo Auxiliary** input with volume control. The **Master Control** division uses an "Global" 3 band EQ, Master volume control and a discrete Headphone jack with its own volume pot.*



Available October 2015

# Leslie LS2215 Specifications

|                                |  |
|--------------------------------|--|
| <b>POWER AMP</b>               | Mono Solid State 200W RMS/300W Peak  |
| <b>PRE-AMP (mini mixer)</b>    | Stereo   |
| <b>FRONT PANEL</b>             |  |
| <b>Master control</b>          | Volume / 3-Band EQ (Low/Mid/High)  |
| <b>Channel Inputs/Control</b>  | 4 + (1) Headphone  |
| <b>Keyboard Channel</b>        |  |
| Input # & Type                 | (1) L & (1) R TR - 1/4" mono each  |
| Effect - Send & Return Control | (1) L & (1) R TRS - 1/4" mono each<br>Volume / 3-Band EQ (Low/Mid/High)  |
| <b>Instrument Channel</b>      |  |
| Input # & Type                 | (1) L & (1) R TR - 1/4" mono each<br>(Passive/Active)  |
| Effect - Send & Return Control | (1) L & (1) R TRS - 1/4" mono each<br>Volume / 3-Band EQ (Low/Mid/High)  |
| <b>Microphone</b>              | (1) XLR & (1) 1/4" mono  |
| Control                        | Volume / 3-Band EQ (Low/Mid/High)  |
| <b>Aux</b>                     | (1) L & (1) R TR - 1/4" mono each  |
| Control                        | Volume   |
| <b>Headphones</b>              | (1) TRS - 1/4" Stereo  |
| Control                        | Volume (independent of main volume)  |
| <b>Nominal Input Level</b>     | (@1kHz, output 10%): Instrument: (Passive) -25dBu, (Active) -19dBu; Mic: (XLR) -38dBu, (1/4") -28dBu; Keyboard -24dBu; Aux: -15dBu |
| <b>REAR PANEL</b>              |  |
| <b>Master Line Out</b>         | Stereo   |
| 2 - sets                       | (1) L & (1) R TR - 1/4" mono each<br>(1) L & (1) R - XLR each w/gnd  |
| Effect - Send & Return         | (1) L & (1) R TRS - 1/4" mono each<br>(Send only provides right channel audio out to slave amp for stereo)                         |
| <b>Nominal Output Level</b>    | (@1kHz): Phone: +15dBu; L&R XLR Balance Out (w/level control) +15 dBu; L&R 1/4" Out +15dBu   |
| <b>SPEAKERS</b>                |  |
| Tweeter                        | 2 X 4" mid - high frequency drivers  |
| Woofer                         | 1 X 15" low frequency driver   |
| Bass Ports                     | 2X Front   |
| <b>AC Input</b>                | 110/120 (50/50 Hz) - 220/240 (50/60 Hz)  |
| <b>WEIGHT</b>                  | 70 lbs.  |
| <b>CABINET FINISH</b>          | Black - Tolex  |
| <b>CABINET SIZE</b>            | 21 5/8" (W) x 13" (D) x 29 3/16 (H)  |
| <b>WARRANTY</b>                | 12-months parts/labor  |
| <b>OPTIONAL ACCESSORY</b>      | Amp Cover (part #003-Leslie2215-cover)<br>Dolly with 4-casters (part #532--059 700)  |

**Hammond USA** 743 Annoreno Drive Addison, IL 60101 USA Tel: 630-543-0277

info@hammondorganco.com - www.hammondorganco.com

