

HAMMOND

THE SOUND THE SOUL THE ONE

HOW TO SEND SKPRO PROGRAM CHANGE IN A DAW

If you're using a DAW like ProTools or Logic, Etc. You may wish to send Program changes to your SkPRO

Here, we'll learn to send the proper MIDI messages to do so

The SkPRO's structure is based on COMBINATIONS

The MIDI messages you send will directly "pull up" either User or Factory Combinations

If you would rather access your FAVORITES, you'll be able to do that too

The COMBINATION CHANGE CHART (PDF) is included in this document. Print it out and keep it at hand for future reference.

Make a note of Which SkPRO Combination you wish to insert in your Sequence/Data Stream

Or: The Current Favorite you are playing (or wish to insert)

Call up the PROGRAM CHANGE window in your DAW for that track (consult your owners manual for your DAW to find this)

You should see 3 Fields to be filled in: PROGRAM CHANGE, MSB, LSB
(There may be more fields in your DAW's Program Change Window. The 3 listed here are the important ones-Consult the Owners Manual of your chosen DAW for further information)

MSB and LSB are MIDI codes for Bank Select

Let's say you'd like to send FACTORY COMBINATION F012 to your DAW App

Enter [012] in the PROGRAM CHANGE area in your DAW's Program Change dialog

Enter "2" in the MSB Area

This insures you will select a FACTORY Combination

If you were selecting a USER COMBINATION (U012), You'd enter a "1" in the MSB Area

Now, Enter "0" in the LSB Area

For SkPRO Program Change operations, the value of LSB will always be "0"

The "LSB" setting is not used in sending PROGRAM CHANGE info for the SkPRO

Run your sequence, and you will see the PROGRAM CHANGE at the location you specify

If you'd like to send the FAVORITE instead of the direct Combination number:

Enter the FAVORITE number using "1" as a prefix in the PROGRAM CHANGE area

Example: If you are sending Favorite "5", you would enter "105"

Now, enter the BANK number following the legend on the COMBINATION CHANGE CHART in the MSB area

Example: Bank 1 value would be "100", Bank 2 would be "101", and so forth

As always, the LSB value will be "0"

Run your Sequence, and you'll see the FAVORITE CHANGE at the location you specify

HAMMOND

THE SOUND THE SOUL THE ONE

TO SEND DIRECT COMBINATION CHANGE:

PROGRAM CHANGE	MSB	LSB
1-100 Combi #	1=USER	0
1-100 Combi #	2=FACT.	0

TO SEND FAVORITES CHANGE:

PROGRAM CHANGE	MSB	LSB
101-110 (Fav # 1-10)	100 (Bank 1)	0
101-110 (Fav # 1-10)	101 (Bank 2)	0
101-110 (Fav # 1-10)	102 (Bank 3)	0
101-110 (Fav # 1-10)	103 (Bank 4)	0
101-110 (Fav # 1-10)	104 (Bank 5)	0
101-110 (Fav # 1-10)	105 (Bank 6)	0
101-110 (Fav # 1-10)	106 (Bank 7)	0
101-110 (Fav # 1-10)	107 (Bank 8)	0
101-110 (Fav # 1-10)	108 (Bank 9)	0
101-110 (Fav # 1-10)	109 (Bank 10)	0